

# 8155W 1/2 HP AC BELT DRIVE WI-FI® GARAGE DOOR OPENER

Dependable performance.



## KEY FEATURES

**QUIET OPERATION**  
Belt Drive

**WI-FI**  
Built In

MyQ® Technology makes this opener compatible with multiple home automation platforms.



Visit [LiftMaster.com/WorksWithMyQ](http://LiftMaster.com/WorksWithMyQ) for a full list of MyQ partners.\*

## RELIABLE

**1/2 HP AC MOTOR** IS PURPOSEFULLY DESIGNED AND BUILT TO LAST.

**BELT DRIVE SYSTEM** FOR QUIET, MAINTENANCE-FREE PERFORMANCE.

**WARRANTY** 4-YEAR MOTOR, 1-YEAR PARTS.

## SMART

**BUILT-IN WI-FI** FOR THE EASIEST WAY TO CONNECT THE GARAGE.

**MyQ MOBILE APP** LETS USERS RECEIVE ALERTS AND CONTROL THE OPENER FROM ANYWHERE.

## SECURE

**SECURITY+ 2.0®** SENDS A NEW CODE WITH EVERY REMOTE CLICK.

**POSILOCK®** ELECTRONICALLY PROTECTS AGAINST FORCED OPENINGS.

**ALERT-2-CLOSE** SIGNALS WHEN A DOOR IS BEING CLOSED BY MyQ.

**THE PROTECTOR SYSTEM®** INVISIBLE LIGHT BEAM AUTO-REVERSES THE DOOR IF THERE IS AN OBSTRUCTION.

## INCLUDED ACCESSORIES:

**MULTI-FUNCTION CONTROL PANEL®**  
Includes lockout controls and accessory programmability.



882LMW

**3-BUTTON REMOTE CONTROL**  
Operates up to 3 openers or MyQ Light Accessories.



893LM

## POWERFUL ADD-ONS:

**MyQ HOME BRIDGE**  
Adds Apple® HomeKit™ compatibility and Siri® voice control to Wi-Fi-enabled openers. Installs easily in the garage within Wi-Fi range.\*\*



819LMB

**MINI UNIVERSAL REMOTE CONTROL**  
Compact and portable to provide quick, easy garage access.



374UT

**REMOTE LIGHT CONTROL**  
Plug in any lamp to this device to control it with a smartphone or garage remote.



825LM

**REMOTE LIGHT SWITCH**  
Replaces an existing wall switch to control home lighting with a smartphone or garage remote.



823LM

**GARAGE DOOR AND GATE MONITOR**  
Monitors and closes up to 4 garage doors from any room in the house.



829LM

\*Linking your MyQ account to a partner may require an additional accessory purchase or subscription fee. Smartphone not included.

\*\*Controlling this HomeKit-enabled accessory automatically and away from home requires an Apple TV® with tvOS™ 10.0 or later or an iPad® with iOS 10.0 or later set up as a home hub.

**PRODUCT GUIDE 8155W**  
1/2 HP AC BELT DRIVE WI-FI  
GARAGE DOOR OPENER

**LiftMaster®**

**8155W**

# MASTERFUL ENGINEERING.

**1/2 HP AC BELT DRIVE WI-FI®  
GARAGE DOOR OPENER**

## MOTOR



- 1/2 Horsepower AC
- 1,625 RPM
- Automatic Thermal Protection
- Permanent Lubrication

## POWER



- 120V AC
- 60 Hz Voltage
- 6A Current Rating
- UL® Listed
- 4' Power Cord (3-Prong)

**5.75"****15"****16"**

## MECHANICS



- **Steel Chassis, T-Rail and Trolley**
- **Full Reinforced Belt Drive Mechanism** (16:1 Gear Reduction and Adjustable Door Arm)
- **Auto-Force** Adjustment for Changing Weather and Environmental Conditions
- **Electronic Limits** for Easy Setup
- **AC Wi-Fi Logic Board** with Built-In Surge Suppressor (for Replacement Logic Boards, Order Part 050ACTWF)

## DIMENSIONS

Rail Options	7'	8'	10'
Installed Length	124"	136"	160"
Max. Opening	7'6"	8'6"	10'6"

Headroom Clearance Required: 2"

**7"**

Per second for door to move upward

## SPEED

**7"**

Per second for door to move downward

# STANDARD SPECS.

## SECURITY

### SECURITY+ 2.0® RADIO CONTROLS

3-Button Remote Control (893LM)

Operating Range: **~200'**Operating Temperature: -30°F to 150°F  
Frequency:

- Remote Control: 310, 315 and 390 MHz Tri-Band
- Garage Door Opener: Frequency Agile on 310, 315 and 390 MHz
- Security+ 2.0 Anti-Burglary Coding

### SECURITY+ 2.0 ENCRYPTED CONTROLS

Multi-Function Control Panel® (882LMW)

- Program Remote Controls
- Maintenance Alert System
- Easy Wi-Fi Setup

## SMART

### MyQ® RADIO

**902-928 MHz**  
50-Channel FHSS  
(Frequency Hopping Spread Spectrum)

- Provides 2-way communication from garage door opener and MyQ Accessories.
- Enables monitoring and control of garage door openers and lighting controls via smartphone, tablet or computer.

## ELECTRICAL

### LIGHTING



- Max. 1 100-Watt Lightbulb
- Enhanced CFL (Compact Fluorescent) Compatible, Max. 26 Watts

### HOMELINK® COMPATIBLE (VERSION 4.0 OR HIGHER\*)

\*May require an external adapter depending on the model and year of your vehicle. Visit [HomeLink.com](http://HomeLink.com) for additional information.

# SHIPPING.

SHIPPING WEIGHT (in lbs.)

**20**  
HEAD**17**  
RAIL (7')

## CARTONS (2)

CARTON 1: 20" x 12" x 10"

- Multi-Function Control Panel (882LMW)
- 3-Button Remote Control (893LM)
- Garage Door Opener Head (8155W)
- The Protector System® Safety Reversing Sensors

CARTON 2: 10'4" x 5" x 5" (for 7' Rail)

- Assembled Solid-Steel Chain T-Rail

# CONVENIENCE AND SAFETY.



- Alert-2-Close with Unattended Close Operation†
- Emergency/Quick Release
- Automatic Trolley Reconnect
- Ventilation/Pet Opening
- Down Safety Reverse
- Up Safety Stop
- Safety Beam Obstruction Turns Lights On
- Maintenance Alert System
- Garage Door Opener Capacity of up to 12 Remote Controls, 1 Keyless Entry System and 16 MyQ Devices

†WARNING: to reduce the risk of injury to persons—  
ONLY enable Timer-to-Close and MyQ remote operation features when opener is installed on a sectional door.

ALARM.COM is a registered service mark of Alarm.com.  
Apple is a trademark of Apple Inc., registered in the U.S. and other countries. HomeKit is a trademark of Apple Inc.  
Clare Controls is a registered trademark of Clare Controls, Inc.  
Google, Google Home, Google Assistant and other related marks and logos are trademarks of Google Inc.  
Nest is a trademark of Nest Labs, Inc.  
XFINITY Home and the XFINITY Home design logo are trademarks or service marks of Comcast Corporation.  
UL and the UL logo are trademarks of UL LLC © 2018 All Rights Reserved.  
Wi-Fi® is a registered trademark of Wi-Fi Alliance  
HomeLink® and the HomeLink House® logo are registered trademarks of Gentex Corporation  
LMGDENPG8155W 3/18